



LED TUBE LT8 TC - 9/24W

LED shatter-proof tube, G13 base

Application

Energy efficient LED lamp solutions

Design Specifications

- Fits new T8 LED fixtures or retrofit T8 fluorescent fixtures (Magnetic Ballast)
- Traditional full glass shatter-proof poly coated body construction, G13 lamp base
- High efficiency SMD LED chips, CRI >80, beam 320°
- Integral non-dimmable LED driver, 9, 18 or 24 watt models
- Colour temperature selectable 3000K / 4000K / 6000K
- No flicker, instant start, Safety LED fuse included, double insulation



Technical Specification

Model No.	Input Voltage (V/AC)	Power (W)	Lumens (lm)	CCT (K)	CRI	Beam Angle (°)
LT8/60TC	240	9	900/1100/1000	3000/4000/6000	80	320
LT8/120TC	240	18	1800/2200/2000	3000/4000/6000	80	320
LT8/150TC	240	24	2300/2500/2400	3000/4000/6000	80	320

Technical Specification

Model No.	Dimmable	Diameter (mm)	Length (mm)	Base Type
LT8/60TC	NO	28	589	G13
LT8/120TC	NO	28	1198	G13
LT8/150TC	NO	28	1500	G13

Warning: The luminaire that these LED tubes are installed in may need to be converted in accordance with AS/NZS60598.2.1:2014 by a suitably qualified person. In all instances any electronic components (i.e. driver, electronic ballast, capacitor) must be removed from the circuit. Refer installation instructions for more details, in particular the orientation of the lamp ACTIVE supply.

IMPORTANT, where CCT selection switching is provided, it is important to switch OFF the SUPPLY before the CCT selection is made,



otherwise equipment damage may occur.

Due to continued product and technology enhancements, data sourced from sal.net.au shall not form part of any contract and or technical performance guarantee unless expressly confirmed in writing by SAL at the time of order. Products are sold in accordance with [SAL Terms and Conditions of sale](#) and all images shown are for illustration purposes only and may vary from the actual colour or finish. Unless specifically stated, all IP ratings nominated for Interior products are from "below the ceiling".

Dimensions

WARNING:

The luminaire that these LED tubes are installed in may need to be converted in accordance with AS/NZS60598.2.1:2014 by a suitably qualified person. In all instances any electronic components (i.e. driver, electronic ballast, capacitor) must be removed from the circuit. Refer installation instructions for more details, in particular the lamp orientation to the ACTIVE supply.

Product Images

WARNING:

The luminaire that these LED tubes are installed in may need to be converted in accordance with AS/NZS60598.2.1:2014 by a suitably qualified person. In all instances any electronic components (i.e. driver, electronic ballast, capacitor) must be removed from the circuit. Refer installation instructions for more details, in particular the lamp orientation to the ACTIVE supply.